Note: This datasheet may be out of date.

Please download the latest datasheet of BLM31KN121BH1# from the official website of Murata Manufacturing

Co., Ltd.

https://www.murata.com/en-eu/products/productdetail?partno=BLM31KN121BH1%23

### BLM31KN121BH1#

"#" indicates a package specification code.










< List of part numbers with package codes >

BLM31KN121BH1B BLM31KN121BH1K BLM31KN121BH1L



### Appearance & Shape







- 1.The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted. BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.
- 2.The nickel barrier structure of the external electrodes provides excellent solder heat resistance.
- 3.BLM31KN series can be used in high current circuits due to its low DC resistance. It can match power lines to a maximum of 4ADC.
- 4.150°C guaranteed.

# Applications

Automotive	Po
Usage	[

Powertrain/Safety



# Packaging Information

Packaging	Specifications	Minimum Order Quantity
В	Bulk(Bag)	1000
К	330mm Embossed Tape	8000
L	180mm Embossed Tape	2500

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated : 2018/05/21



Co., Ltd. https://www.murata.com/en-eu/products/productdetail?partno=BLM31KN121BH1%23

### $\underline{ Please \ download \ the \ latest \ data sheet \ of \ BLM31KN121BH1\# \ from \ the \ official \ website \ of \ Murata \ Manufacturing} }$

# BLM31KN121BH1#

"#" indicates a package specification code.

Number of Circuit

Note: This datasheet may be out of date



Shape	SMD
Size Code (in mm)	3216
Size Code (in inch)	1206
Length	3.2mm
Length Tolerance	±0.2mm
Width	1.6mm
Width Tolerance	±0.2mm
Thickness	1.6mm
Thickness Tolerance	±0.2mm
Impedance (at 100MHz)	120Ω
Impedance (at 100MHz) Tolerance	±25%
Rated Current (at 85°C)	4A
Rated Current (at 125°C)	4A
Rated Current (at 150°C)	10mA
DC Resistance(max.)	0.009Ω
Operating Temperature Range	-55°C to 150°C
Mass(typ.)	0.041g

2 of 3

#### Attention

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/


Last updated : 2018/05/21

<sup>1.</sup> This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

## BLM31KN121BH1#


"#" indicates a package specification code.






In operating temperature exceeding +125°C, derating of current is necessary for BLM31KN\_BH1 series. Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



Impedance-Frequency Characteristics



**Derating of Rated Current** 

**Equivalent Circuit** 

3 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

